

CWT-MB317E

Modbus I O Module

manual


CONTENTS

- 1 OVERVIEW 3
 - 1.1 SYSTEM PARAMETER 3
- 2 INSTALL 4
 - 2.1 SIZE 4
 - 2.2 WIRING 5
- 3 CONFIGURATION 6
 - 3.1 RS232/RS485 6
 - 3.2 CONFIGURATION SOFTWARE 7
 - 3.3 ETHERNET 7
- 4 DESCRIPTION OF IO CHANNEL 8
 - 4.1 DIGITAL INPUT 8
 - 4.2 DIGITAL OUTPUT 9




1 OVERVIEW

Model	Options	IO Port	Communication Port	Protocol
CWT-MB317E	485	8DI+8DO (NPN)	RS485	Modbus RTU
	485-232	8DI+8DO (NPN)	RS485+RS232	Modbus RTU
	E	8DI+8DO (NPN)	Ethernet	Modbus TCP
	E-485-232	8DI+8DO (NPN)	Ethernet+RS485+RS232	Modbus TCP, Modbus RTU




1.1 System Parameter

CPU	32-bit ATMEL ARM, 72MHZ
OS	GCOS, 10ms scheduling mechanism
Power	7-35VDC @2W, power supply reverse protection, isolation design
Installation	DIN rail mounting or screw fixing 
Working Environment	-40℃～85℃, 5%～95%RH(non-condensing)
Protection	IP20
Watchdog	1.5m guard

2 INSTALL

2.1 size



2.2 wiring




3 CONFIGURATION

3.1 RS232/RS485

Port type	1RS485 & 1RS232
Protection	DCDC isolation design, 2500V lightning protection, ESD, overvoltage, overcurrent protection
Baud rate	1200~115200, default 9600
Parity	Even, Odd, None
start bit	1 bit
data bits	8 bit
Stopbits	1,2bits
Protocol	MODBUS RTU
default	9600.N.8.1, slave id is 1



3.2 Configuration software



Set salve ID, default is 1

3.3 Ethernet

Port type	RJ45
Communicate protocol	MODBUS TCP、MODBUS UDP
Communicate rate	1000 times/s
bandwidth	10M/100Mbps
IP address	192.168.1.75
Port	502

4 DESCRIPTION OF IO CHANNEL

4.1 Digital input


ON signal level	5-30VDC, 6mA@24VDC
OFF signal level	0-3VDC
Protection	opt coupler isolation, 2500V lightning protection, overvoltage, overcurrent protection
Sample rate	0.01m

Modbus Register map


channel	Register address
DI0-DI7	10001-10008

DI wiring diagram

Wet contact wiring



Dry contact wiring



4.2 Digital output

Output type	NPN transistor output
Isolation	opt coupler isolation
Load voltage	5-30VDC
Load current	100mA

Modbus Register map

channel	Register address
Do0-Do7	00001-00008

DO wiring diagram

