

CWT-MB318W

Modbus I O Module

manual


CONTENTS

- 1 OVERVIEW 3
 - 1.1 SYSTEM PARAMETER 3
- 2 INSTALL 4
 - 2.1 SIZE 4
 - 2.2 WIRING 5
- 3 CONFIGURATION 6
 - 3.1 RS232/RS485 6
 - 3.2 CONFIGURATION SOFTWARE 7
- 4 DESCRIPTION OF IO CHANNEL 8
 - 4.1 ANALOG INPUT 8
 - 4.2 DIGITAL INPUT 9
 - 4.3 PT100 INPUT 10




1 OVERVIEW

Model	Options	IO Port	Communication Port	Protocol
CWT-MB318W	I-V-E	8PT + 8AI (4-20mA/0-10V) + 8DI	Ethernet	Modbus TCP
	I-V-E-485	8PT + 8AI (4-20mA/0-10V) + 8DI	Ethernet+RS485	Modbus TCP, Modbus RTU
	I-V-E-485-232	8PT + 8AI (4-20mA/0-10V) + 8DI	Ethernet+RS485+RS232	Modbus TCP, Modbus RTU




1.1 System Parameter


CPU	32-bit ATMEL ARM, 72MHZ
OS	GCOS, 10ms scheduling mechanism
Power	7-35VDC @2W, power supply reverse protection, isolation design
Installation	DIN rail mounting or screw fixing 
Working Environment	-40℃~85℃, 5%~95%RH(non-condensing)
Protection	IP20
Watchdog	1.5m guard

2 INSTALL

2.1 size





2.2 wiring




3 CONFIGURATION

3.1 RS232/RS485

Port type	1RS485 & 1RS232
Protection	DCDC isolation design, 2500V lightning protection, ESD, overvoltage, overcurrent protection
Baud rate	1200~115200, default 9600
Parity	Even, Odd, None
start bit	1 bit
data bits	8 bit
Stopbits	1,2bits
Protocol	MODBUS RTU
default	9600.N.8.1, slave id is 1



3.2 Configuration software



Set slave ID, default is 1

3.3 Ethernet

Port type	RJ45
Communicate protocol	MODBUS TCP、MODBUS UDP
Communicate rate	1000 times/s
bandwidth	10M/100Mbps
IP address	192.168.1.75
Port	502

4 DESCRIPTION OF IO CHANNEL


4.1 Analog input

Input type	4~20mA<default>, support: 0~20mA/0~5/1~5/0~10V (need open housing to jumper)
Precision	0.1%, 16 bit
Refresh rate	0.01m

Modbus Register map

channel	Register address	Function code	Format	Scaling
AI0-AI7	40059-40066	03	UINT16	0.001

AI wiring diagram



4.2 Digital input


ON signal level	5-30VDC, 6mA@24VDC
OFF signal level	0-3VDC
Protection	opt coupler isolation, 2500V lightning protection, overvoltage, overcurrent protection
Sample rate	0.01m

Modbus Register map


channel	Register address
DI0-DI7	10001-10008

DI wiring diagram

Wet contact wiring



Dry contact wiring




4.3 PT100 Input

Input type	PT100
Precision	0.1°C
Measurement range	-200°C~220°C

Modbus Register map

channel	Register address	Function code	Format	Scaling
PT0-PT7	40051-40058	04	signed UINT16	0.1

Three wire



Two wire

